

Low-cost shaping of electrical stimulation waveforms for bioelectronic medicine with improved efficiency and selectivity

Rashidi, Amin; Varkevisser, Francesc; Giagka, Vasiliki; Costa, Tiago L.; Serdijn, Wouter A.

Publication date

2023

Document Version

Final published version

Citation (APA)

Rashidi, A., Varkevisser, F., Giagka, V., Costa, T. L., & Serdijn, W. A. (2023). *Low-cost shaping of electrical stimulation waveforms for bioelectronic medicine with improved efficiency and selectivity*.

Important note

To cite this publication, please use the final published version (if applicable).
Please check the document version above.

Copyright

Other than for strictly personal use, it is not permitted to download, forward or distribute the text or part of it, without the consent of the author(s) and/or copyright holder(s), unless the work is under an open content license such as Creative Commons.

Takedown policy

Please contact us and provide details if you believe this document breaches copyrights.
We will remove access to the work immediately and investigate your claim.

LOW-COST SHAPING OF ELECTRICAL STIMULATION WAVEFORMS FOR BIOELECTRONIC MEDICINE WITH IMPROVED EFFICIENCY AND SELECTIVITY

Amin Rashidi, Francisc Varkevisser, Vasiliki Giagka, Tiago L. Costa, and Wouter A. Serdijn

*Section Bioelectronics, dept. Microelectronics, Delft University of Technology,
Mekelweg 4, 2628 CD Delft,
The Netherlands*

ABSTRACT

Electrical stimulation is proven to be an effective way of neuromodulation in bioelectronic medicine (e.g. cochlear implants, deep brain stimulators, etc.), delivering localized treatment by the means of electrical pulses. To increase the stimulation efficiency and neural-type selectivity, there is an increasing interest to employ non-rectangular stimulation waveforms [1-4]. Even though delivering and storing digital data at the stimulator provides the highest flexibility for generating stimulation waveforms, state-of-the-art approaches suffer either from poor resolution or the requirement of high data bandwidth for wirelessly powered implants [2]. Using Analog waveform generators is an alternative approach at the cost of extra implementation complexity for each type of waveform [3].

To fulfill the same goals as employing arbitrary waveforms for stimulation, we propose to shape the typical rectangular waveform using a programmable first-order low-pass filter, mimicking the natural filtering characteristic of the neural membrane. Using bio-realistic modeling, we show that such a pre-filtered waveform requires less or equal energy for the activation of neurons when compared with other energy-efficient waveforms (e.g. Gaussian). Notably, this comes at the low cost of only one extra programmable parameter (i.e., the filter's corner frequency), on top of the typical duration and amplitude parameters.

The basic concept of this work is driven by the fact that the natural low-pass characteristic of the neuron's membrane limits the energy transfer efficiency from the stimulator to the cell. Thus, it is proposed to pre-filter the high-frequency components of the stimulus [4]. The method is validated for a Hodgkin-Huxley (HH) axon-cable model using NEURON v8.0 software. The required activation energy is simulated for rectangular, Gaussian, half-sine, triangular, ramp-up, and ramp-down waveforms, all with pulse durations of 10-1000 μ s, and low-pass filtered with cut-off frequencies of 0.5-50kHz. Simulations show a 51.5% reduction in the required activation energy for the shortest rectangular pulse (i.e., 10- μ s pulse width) after filtering at 5kHz. It is also shown that the minimum required activation energy can be decreased by 11.04%, 9.49%, 8.28%, 1.81%, 0.17%, and 0% when an appropriate pre-filter is applied to the rectangular, ramp-down, ramp-up, half-sine, triangular, and Gaussian waveforms, respectively. Finally, a perspective usage of this method to improve the selectivity of electrical stimulation is drawn.

References:

- [1] K. Kolovou-Kouri, A. Rashidi, F. Varkevisser, W. A. Serdijn, and V. Giagka, "Energy savings of multi-channel neurostimulators with non-rectangular current-mode stimuli using multiple supply rails," in *2022 44th Annual International Conference of the IEEE Engineering in Medicine & Biology Society (EMBC)*, 2022, pp. 3443–3446.
- [2] G. O'Leary, D. M. Groppe, T. A. Valiante, N. Verma, and R. Genov, "Nurip: Neural interface processor for brain-state classification and programmable-waveform neurostimulation," *IEEE Journal of Solid-State Circuits*, vol. 53, no. 11, pp. 3150–3162, 2018.
- [3] M. H. Maghami, A. M. Sodagar, and M. Sawan, "Versatile stimulation back-end with programmable exponential current pulse shapes for a retinal visual prosthesis," *IEEE Transactions on Neural Systems and Rehabilitation Engineering*, vol. 24, no. 11, pp. 1243–1253, 2016.
- [4] F. Varkevisser, A. Rashidi, T. L. Costa, V. Giagka, and W. A. Serdijn, "Pre-Filtering of Stimuli for Improved Energy Efficiency in Electrical Neural Stimulation," in *Proceedings of 2022 IEEE Biomedical Circuits and Systems Conference (BioCAS)*, 2022, in press.